

On/Off, Floating Point, Non-Spring Return, Linear, AC 100...240 V







Tecl			_	-	
100	4141	100211	-	m	12

Nominal voltage	AC 100240 V
Nominal voltage frequency	50/60 Hz
Power consumption in operation	2.5 W
Power consumption in rest position	0.5 W
Transformer sizing	4.5 VA (class 2 power source)
Electrical Connection	18 GA appliance cables, 3 ft [1 m], 10 ft [3 m] or 16ft [5 m], with 1/2" conduit connector
Overload Protection	electronic throughout full stroke
Actuating force motor	450 N [100 lbf]
Direction of motion motor	reversible with switch
Manual override	external push button
Stroke	12" [300 mm]
Running Time (Motor)	150 s / 100 mm
Noise level, motor	35 dB(A)
Degree of protection IEC/EN	IP54
Degree of protection NEMA/UL	NEMA 2
Enclosure	UL Enclosure Type 2
Agency Listing	cULus acc. to UL60730-1A/-2-14, CAN/CSA E60730-1:02, CE acc. to 2014/30/EU and 2014/35/EU; Listed to UL 2043 - suitable for use in air plenums per Section 300.22(c) of the NEC and Section 602.2 of the IMC
Quality Standard	ISO 9001
Ambient temperature	-22122°F [-3050°C]
Storage temperature	-40176°F [-4080°C]
Ambient humidity	Max. 95% RH, non-condensing
Servicing	maintenance-free
	2.0 - [4.2]
Weight	2.9 lb [1.3 kg]
	Nominal voltage frequency Power consumption in operation Power consumption in rest position Transformer sizing Electrical Connection Overload Protection Actuating force motor Direction of motion motor Manual override Stroke Running Time (Motor) Noise level, motor Degree of protection IEC/EN Degree of protection NEMA/UL Enclosure Agency Listing Quality Standard Ambient temperature Storage temperature Ambient humidity Servicing

Footnotes †Rated Impulse Voltage 800V, Type of Action 1, Control Pollution Degree 2.

Product features

Application

For on/off and floating point control of dampers in HVAC systems. Actuator sizing should be done in accordance with the damper manufacturer's specifications.



Operation

The actuator is not provided with and does not require any limit switches, but is electronically protected against overload. The anti-rotation strap supplied with the actuator will prevent lateral movement.

The AHX... series provides 4, 8, or 12 inches of linear stroke. The stroke of the gear rack can be adjusted on both sides in increments of 0.8 in [20 mm] by means of the mechanical end stops.

When reaching the damper or actuator end position, the actuator automatically stops.

The gears can be manually disengaged with a button on the actuator cover.

The AHX120-3... actuators use a sensorless brushless DC motor, which is controlled by an Application Specific Integrated Circuit (ASIC). The ASIC monitors and controls the actuator's rotation and provides a digital rotation sensing (DRS) function to prevent damage to the actuator in a stall condition. Power consumption is reduced in holding mode.

Typical specification

Floating point, on/off control damper actuators shall be electronic type, with integrated linear stroking arm. Actuators shall have brushless DC motor technology and be protected from overload at all positions of linear stroke. Actuators shall have reversing switch and manual override on the cover. Run time shall be constant and independent of torque. Actuators shall be cUL listed, have a 5-year warranty, and be manufactured under ISO 9001 International Quality Control Standards. Actuators shall be as manufactured by Belimo.

Accessories

Electrical accessories	Description	Туре
	Cable conduit connector 1/2"	TF-CC US
Mechanical accessories	Description	Туре
	Ball joint suitable for damper crank arm KH8 / KH10, Multipack 10 pcs.	KG10A
	Ball joint suitable for damper crank arm KH8, Multipack 10 pcs.	KG6
	Ball joint suitable for damper crank arm KH8, Multipack 10 pcs.	KG8
	Push rod for KG6 & KG8 ball joints (36" L, 5/16" diameter).	SH8
	Rotary support, for linear actuator, for compensation of transverse forces	Z-DS1
	3/8"-16 shaft clevis for AHK/AH.	Z-KSC
	Bracket for AHK/AH/LH linear actuators.	ZG-119

Electrical installation





Wht (3)

A) Actuators with appliance cables are numbered.

Actuators may be connected in parallel if not machanical

 $\overline{\lambda}$ Actuators may be connected in parallel if not mechanically linked. Power consumption and input impedance must be observed.







Dimensions

