


Functional Devices, Inc. 101 Commerce Drive, Sharpsville, IN 46068

Email: sales@functionaldevices.com | Website: www.functionaldevices.com **Toll Free:** (800) 888-5538 Office: (765) 883-5538 | Fax: (765) 883-7505

## **RELAY & AC CURRENT SWITCH COMBO**

## **RIBHX24BA**

Current Switch and Relay Combination, 20 Amp SPST-N/O, Adjustable, 24 Vac/dc Coil, NEMA 1 Housing













## **SPECIFICATIONS**

Expected Relay Life: 10 million cycles minimum mechanical

Operating Temperature: -30 to 140° F

Humidity Range: 5 to 95% (noncondensing)

Operate Time: 20ms

**Relay Status:** Red or Green LED On = Activated

**Current Sensor Status** Green LED On = Current Over Trip Point Adjustable

**Dimensions:** 1.70"H x 2.80"W x 1.50"D with 0.50" NPT nipple **Housing Detail:** See **Housing A** in housing guide for dimensions

Origin: Made of US and non-US parts

Wire Length: 16", 600V Rated

Approvals: UL Listed, UL916, C-UL, CE, RoHS Housing Rating: UL Accepted for Use in Plenum, NEMA 1

Gold Flash: No

**Contact Ratings:** 

20 Amp Resistive @ 277 Vac

20 Amp Ballast @ 277 Vac

10 Amp Tungsten @ 120 Vac (N/O)

1,110 VA Pilot Duty @ 277 Vac 770 VA Pilot Duty @ 120 Vac

2 HP @ 277 Vac

1 HP @ 120 Vac

Sensor Type: Internal, with contact status

Sensor Threshold: Adjustable Sensor Range: .25-20 Amps

Sensor Feedback Output: Solid State Contact 30 Vac/dc, 100 mA

**Sensor Contact:** 

• When current sensor status is off (open), leakage <30 uA @ 30Vac/dc

16 Amp Electronic Ballast @ 277 Vac (N/O) • When current sensor status is on (closed), voltage drop

< .3 Vac/dc @ .1 Amp

Coil Current:

128 mA @ 24 Vac 71 mA @ 30 Vdc

Coil Voltage Input:

24 Vac ; 50-60 Hz Drop Out = 3 Vac Pull In = 18 Vac