

# Wireless Relay Kit

The iO Systems wireless relay is perfect for situations where you can't run wire or the existing wire between two devices has been cut or damaged. Now those two devices can communicate wirelessly. The iO-WR Wireless Relay Kit contains 2 four-channel transceivers. The base module has 3 transmitting channels and 1 receiving channel. The satellite module has 3 receiving channels and 1 transmitting channel. Each transceiver module uses a redundant transmission protocol for failsafe protection. If either module does not receive a valid "ON" or "OFF" transmission signal within 60 seconds, the output(s) will be turned off.

**Warranty:** 1 year



## Specifications: Base Module

Dimensions	5 1/8" Height x 2 5/8" Width x 1 1/8" Depth
Input Voltage	24 VAC
Channels	4 channels (3 send, 1 receive)
Contact Rating	1A per channel
Addresses	Unlimited kits can be installed in the same building
Frequency	915MHz proprietary protocol
Range	100' from satellite module depending on building type

## Specifications: Satellite Module

Dimensions	5 1/8" Height x 2 5/8" Width x 1 1/8" Depth
Input Voltage	24 VAC
Channels	4 channels (1 send, 3 receive)
Contact Rating	1A per channel
Addresses	Unlimited kits can be installed in the same building
Frequency	915MHz proprietary protocol
Range	100' from base module depending on building type

5351 East Thompson Road Suite 142  
 Indianapolis, IN 46237  
 P: 888.359.0362  
 F: 317.489.5204  
 info@iOhvacsystems.com  
 www.iOhvacsystems.com

