



Rack PDU, Basic, Zero U, 15A, 100/120V, (14) 5-15

AP9567

Call for More Information 800-800-4272

- APC Basic Rack PDUs distribute reliable rack power distribution via a single input with multiple output receptacles. Easily mount this vertical PDU in racks or enclosures. It occupies zero U of valuable rack space, which allows space for more equipment in the rack. This vertical PDU does not require additional tools to mount into APC NetShelter Enclosures. Enables a quick recovery from overload events. Packaging Includes PDU, Installation guide, Rack Mounting brackets, Toolless Mounting Kit.
- Includes: Installation guide, Rack mounting brackets, Toolless mounting kit

Output	
Nominal Output Voltage	100V, 120V
Overload Protection	Yes
Maximum Total Current Draw	15
Output Connections	(14) NEMA 5-15R

Input	
Nominal Input Voltage	100V, 120V
Input frequency	50/60 Hz
Input Connections	NEMA 5-15P
Cord Length	12.01ft (3.7meters)
Acceptable Input Voltage	100 - 125VAC
Number of Power Cords	1
Load Capacity	1400VA
Maximum Input Current	15A
Regulatory Derated Input Current (North 12A America)	

Physical	
Maximum Height	24.02inches (610MM, 61.0CM)
Maximum Width	1.73inches (44MM, 4.4CM)
Maximum Depth	1.73inches (44MM, 4.4CM)
Net Weight	4.81lbs. (2.18KG)

Disclaimer: Documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user's applications.



Physical	
Shipping weight	6.44lbs. (2.92KG)
Shipping Height	25.51inches (648MM, 64.8CM)
Shipping Width	7.01inches (178MM, 17.8CM)
Shipping Depth	5.98inches (152MM, 15.2CM)
Color	Black

Environmental	
Operating Temperature	32 - 113 °F (0 - 45 °C)
Operating Relative Humidity	0 - 95 %
Operating Elevation	0 - 10000ft (0 - 3048meters)
Storage Temperature	-25 - 65 °C
Storage Relative Humidity	0 - 95 %
Storage Elevation	0 - 50000ft (0 - 15240meters)

Conformance	
Approvals	cUL listed, METI Denan, UL listed
Standard warranty	2 years repair or replace

Sustainable Offer Status	
RoHS	Compliant
PEP	Available in Documentation tab
EOLI	Available in Documentation tab

Disclaimer: Documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user's applications.