

MFT/programmable, Non fail-safe, 24 V





Technical data

| Electrical data | Nominal voltage | AC/DC 24 V |
|-----------------|------------------------------------|---|
| | Nominal voltage frequency | 50/60 Hz |
| | Nominal voltage range | AC 19.228.8 V / DC 21.628.8 V |
| | Power consumption in operation | 3.5 W |
| | Power consumption in rest position | 1.3 W |
| | Transformer sizing | 6 VA |
| | Electrical Connection | 18 GA plenum cable, 3 ft [1 m], with 1/2" NPT conduit connector (10 ft [3 m] and 16 ft [5 m] available) |
| | Overload Protection | electronic throughout 095° rotation |
| Functional data | Operating range Y | 210 V |
| | Operating range Y note | 420 mA w/ ZG-R01 (500 Ω, 1/4 W resistor) |
| | Input impedance | 100 k Ω for 210 V (0.1 mA), 500 Ω for 420 mA, 1500 Ω for PWM, On/Off and Floating point |
| | Operating range Y variable | Start point 0.530 V |
| | | End point 2.532 V |
| | Operating modes optional | variable (VDC, PWM, on/off, floating point) |
| | Position feedback U | 210 V |
| | Position feedback U note | Max. 0.5 mA |
| | Position feedback U variable | VDC variable |
| | Direction of motion motor | selectable with switch 0/1 |
| | Manual override | external push button |
| | Angle of rotation | Max. 95° |
| | Angle of rotation note | adjustable with mechanical stop |
| | Running Time (Motor) | 150 s / 90° |
| | Running time motor variable | 90350 s |
| | Noise level, motor | 45 dB(A) |
| | Position indication | Mechanical, integrated, two-section |
| Safety data | Degree of protection IEC/EN | IP54 |
| | Degree of protection NEMA/UL | NEMA 2 |
| | Enclosure | UL Enclosure Type 2 |
| | Agency Listing | cULus acc. to UL60730-1A/-2-14, CAN/CSA E60730-1:02 CE acc. to 2014/30/EU and 2014/35/EU |
| | Quality Standard | ISO 9001 |
| | <u></u> | |



| Safety data | UL 2043 Compliant | Suitable for use in air plenums per Section 300.22(C) of the NEC and Section 602 of the IMC |
|-------------|---------------------|---|
| | Ambient humidity | Max. 95% RH, non-condensing |
| | Ambient temperature | -22149°F [-3065°C] |
| | Storage temperature | -40176°F [-4080°C] |
| | Servicing | maintenance-free |
| Weight | Weight | 1.8 lb [0.83 kg] |
| Materials | Housing material | Galvanized steel and plastic housing |

Footnotes TRated Impulse Voltage 800V, Type action 1, Control Pollution Degree 3.

Accessories

| Description | Туре |
|---|---|
| Battery backup system, for non-spring return models | NSV24 US |
| Battery, 12 V, 1.2 Ah (two required) | NSV-BAT |
| Service tool, with ZIP-USB function, for programmable and | ZTH US |
| | |
| | Battery backup system, for non-spring return models Battery, 12 V, 1.2 Ah (two required) |

Electrical installation

K INSTALLATION NOTES

- Actuators with appliance cables are numbered.
- Provide overload protection and disconnect as required.
- Actuators may also be powered by DC 24 V.
- S Only connect common to negative (-) leg of control circuits.
- A 500 Ω resistor (ZG-R01) converts the 4...20 mA control signal to 2...10 V.
- Control signal may be pulsed from either the Hot (Source) or Common (Sink) 24 V line.
- For triac sink the Common connection from the actuator must be connected to the Hot connection of the controller. Position feedback cannot be used with a triac sink controller; the actuator internal common reference is not compatible.
- Actuators may be connected in parallel if not mechanically linked. Power consumption and input impedance must be observed.



- \Lambda IN4004 or IN4007 diode. (IN4007 supplied, Belimo part number 40155).
 - Meets cULus requirements without the need of an electrical ground connection.

/ Warning! Live electrical components!

During installation, testing, servicing and troubleshooting of this product, it may be necessary to work with live electrical components. Have a qualified licensed electrician or other individual who has been properly trained in handling live electrical components perform these tasks. Failure to follow all electrical safety precautions when exposed to live electrical components could result in death or serious injury.



Electrical installation

