







## **Technical data**

|            | • 1  |    |     |
|------------|------|----|-----|
| <br>lectri | וראו | n: | בדנ |
|            |      |    |     |

| Nominal voltage                     | AC/DC 24 V   |
|-------------------------------------|--|
| Nominal voltage frequency           | 50/60 Hz   |
| Power consumption in operation      | 7.5 W  |
| Power consumption in rest position  | 3 W  |
| Transformer sizing                  | 10 VA (class 2 power source)   |
| Auxiliary switch                    | 2 x SPDT, 3 A resistive (0.5 A inductive) @ AC 250 V, one set at 10°, one adjustable 1090° |
| Switching capacity auxiliary switch | 3 A resistive (0.5 A inductive) @ AC 250 V   |
| Electrical Connection               | (2) 18 GA appliance cables with 1/2" conduit connectors, 3 ft [1 m],                       |
| Overload Protection                 | electronic throughout 095° rotation  |
| Operating range Y                   | 210 V  |
| Operating range Y note              | 420 mA w/ ZG-R01 (500 Ω, 1/4 W resistor)   |
| Input Impedance                     | 100 kΩ for 210 V (0.1 mA), 500 Ω for 420   |

## **Functional data**

|                               | connectors, s it [1 m],  |
|-------------------------------|--|
| Overload Protection           | electronic throughout 095° rotation  |
| Operating range Y             | 210 V  |
| Operating range Y note        | 420 mA w/ ZG-R01 (500 Ω, 1/4 W resistor)   |
| Input Impedance               | 100 k $\Omega$ for 210 V (0.1 mA), 500 $\Omega$ for 420 mA, 1500 $\Omega$ for PWM, On/Off and Floating point |
| Operating range Y variable    | Start point 0.530 V<br>End point 2.532 V   |
| Options positioning signal    | variable (VDC, PWM, on/off, floating point)  |
| Position feedback U           | 210 V  |
| Position feedback U note      | Max. 0.5 mA  |
| Position feedback U variable  | VDC variable   |
| Direction of motion motor     | selectable with switch   |
| Direction of motion fail-safe | reversible with cw/ccw mounting  |
| Manual override               | 5 mm hex crank (3/16" Allen), supplied   |
| Angle of rotation             | 90°  |
| Running Time (Motor)          | 150 s / 90°  |
| Running time motor variable   | 70220 s  |
| Running time fail-safe        | <20 s  |
| Angle of rotation adaptation  | off (default)  |
| Override control              | MIN (minimum position) = 0%  |
|                               | MID (intermediate position) = 50%  |
|                               | MAX (maximum position) = 100%  |
| Noise level, motor            | 45 dB(A)   |
| Noise level, fail-safe        | 62 dB(A)   |
| Position indication           | Mechanical   |
| Design of superstant IEC/EN   | IDCC   |

# Safety data

| - Contion indication         | Mechanical           |  |
|------------------------------|----------------------|--|
| Degree of protection IEC/EN  | IP66                 |  |
| Degree of protection NEMA/UL | NEMA 4X              |  |
| Enclosure                    | UL Enclosure Type 4X |  |



|             | Technical data sheet     | AFRX24-MFT-S N4   |
|-------------|--------------------------|---|
| Safety data | Agency Listing           | cULus acc. to UL60730-1A/-2-14, CAN/CSA<br>E60730-1:02, CE acc. to 2014/30/EU and<br>2014/35/EU |
|             | Quality Standard         | ISO 9001  |
|             | Ambient temperature      | -22122°F [-3050°C]  |
|             | Ambient temperature note | -4050°C for actuator with integrated heating  |
|             | Storage temperature      | -40176°F [-4080°C]  |
|             | Ambient humidity         | Max. 100% RH  |
|             | Servicing                | maintenance-free  |
|             | Ambient humidity         | Max. 100% RH  |

Die cast aluminium and plastic casing

†Rated Impulse Voltage 800V, Type of action 1.AA, Control Pollution Degree 3 **Footnotes** 

| Accessories                |   |                              |
|----------------------------|---|------------------------------|
| Gateways                   | Description   | Туре                         |
|                            | Gateway MP to BACnet MS/TP  | UK24BAC                      |
|                            | Gateway MP to Modbus RTU  | UK24MOD                      |
|                            | Gateway MP to LonWorks  | UK24LON                      |
| Electrical accessories     | Description   | Туре                         |
|                            | Service Tool, with ZIP-USB function, for programmable and communicative Belimo actuators, VAV controller and HVAC performance devices | ZTH US                       |
| Service tools              | Description   | Туре                         |
|                            | Connection cable 10 ft [3 m], A: RJ11 6/4 ZTH EU, B: 3-pin Weidmüller and supply connection   | ZK4-GEN                      |
|                            | Service Tool, with ZIP-USB function, for programmable and communicative Belimo actuators, VAV controller and HVAC performance devices | ZTH US                       |
| Factory add-on option only | Description   | Туре                         |
|                            | Heater, with adjustable thermostat  | N4 Heater Add-on<br>24V (-H) |

#### **Electrical installation**



Materials

Housing material

### X INSTALLATION NOTES

A Actuators with appliance cables are numbered.

The Provide overload protection and disconnect as required.

 $\mathbf{A}$  Actuators may also be powered by DC 24 V.

Two built-in auxiliary switches (2x SPDT), for end position indication, interlock control, fan startup, etc.

 $\searrow$  Only connect common to negative (-) leg of control circuits.

 $\Lambda$  A 500  $\Omega$  resistor (ZG-R01) converts the 4...20 mA control signal to 2...10 V.

(Source) or Common (Sink) 24 V line.

IN4004 or IN4007 diode. (IN4007 supplied, Belimo part number 40155).

For triac sink the Common connection from the actuator must be connected to the Hot connection of the controller. Position feedback cannot be used with a triac sink controller; the actuator internal common reference is not compatible.

Actuators are provided with a numbered screw terminal strip instead of a cable.

Actuators may be controlled in parallel. Current draw and input impedance must be observed. Master-Slave wiring required for piggy-back applications. Feedback from Master to control input(s) of Slave(s).

Meets cULus requirements without the need of an electrical ground connection.

## Warning! Live electrical components!

During installation, testing, servicing and troubleshooting of this product, it may be necessary to work with live electrical components. Have a qualified licensed electrician or other individual who has been properly trained in handling live electrical components perform these tasks.



Failure to follow all electrical safety precautions when exposed to live electrical components could result in death or serious injury.

A

Apply only AC line voltage or only UL-Class 2 voltage to the terminals of auxiliary switches. Mixed or combined operation of line voltage/safety extra low voltage is not allowed.

