

Functional Devices, Inc. 101 Commerce Drive, Sharpsville, IN 46068

Email: sales@functionaldevices.com | Website: www.functionaldevices.com Office: (765) 883-5538 | Fax: (765) 883-7505 Toll Free: (800) 888-5538

20 AMP POWER CONTROL RELAYS

RIB2401SB

Wht/RIk

120 Vac

Wht/Blu


24 Vac/do

Wht/Yel

Power Relay, 20 Amp SPST-N/O + Override, 24 Vac/dc/120 Vac Coil, NEMA 1 Housing

RIB2402SB

Power Relay, 20 Amp SPST-N/O + Override, 24 Vac/dc/208-277 Vac Coil, NEMA 1 Housing













SPECIFICATIONS

Relays & Contact Type: One (1) SPST Continuous Duty Coil Expected Relay Life: 10 million cycles minimum mechanical

CLOSED OPEN AUTO

Operating Temperature: -30 to 140° F

Humidity Range: 5 to 95% (noncondensing)

Operate Time: 18ms

Relay Status: LED On = Activated

Dimensions: 2.390"H x 3.310"W x 1.810"D with .50" NPT Nipple **Housing Detail:** See **Housing B** in housing guide for dimensions

Origin: Made of US and non-US parts

Wires: 16", 600V Rated

Approvals: UL Listed, UL916, UL864, C-UL

California State Fire Marshal, CE, RoHS

Housing Rating: UL Accepted for Use in Plenum, NEMA 1

Gold Flash: No Override Switch: Yes

Contact Ratings:

Org

Org

CLOSED OPEN AUTO

20 Amp Resistive @ 277 Vac 20 Amp Ballast @ 277 Vac (N/O) 10 Amp Ballast @ 277 Vac (N/C) Not rated for Electronic Ballast 10 Amp Tungsten @ 120 Vac (N/O) 770 VA Pilot Duty @ 120 Vac 1,110 VA Pilot Duty @ 277 Vac

2 HP @ 277 Vac 1 HP @ 120 Vac

Coil Voltage Input:

24 Vac/dc; 120 Vac; 50-60 Hz (RIB2401SB) 24 Vac/dc; 208-277 Vac; 50-60 Hz (RIB2402SB)

Drop Out = $2.1 \, \text{Vac} / 3.8 \, \text{Vdc}$ Pull In = 18 Vac / 22 Vdc

Coil Current:

50 mA @ 18 Vac

83 mA @ 24 Vac

47 mA @ 120 Vac (RIB2401SB) 69 mA @ 208-277 Vac (RIB2402SB)

33 mA @ 22 Vdc 35 mA @ 24 Vdc

47 mA @ 30 Vdc

• Order Normally Closed by adding "-NC"

to end of model number