

## **Engineering Specifications**

### **Hawkeye Current Sensor Model H900**

1. The current sensor shall be induced powered from the monitored load
2. The current sensor shall provide on/off status indication of electrical loads from 1.5 to 200 A
3. The current sensor shall have an auto adjusting operating range from 1.5-200 A
4. The current sensor switch point shall be fixed at 1.5A
5. The current sensor shall be capable of providing accurate status at temperatures from -15 to 60 ° C
6. The current sensor shall be isolated to 600 VAC RMS
7. The current sensor output shall be N.O., Solid State, 0.1 A @ 30 VAC/DC
8. The current sensor shall be a self gripping split-core type with a hole size of (LxW) 1.10"x0.90"
9. The current sensor dimensions shall be (LxWxH)...2.90"X2.58"X1.04"
10. The current sensor shall be a Hawkeye model H900